



## Hidden Menus

Using the LiFeBlue Bluetooth App, you can rename each battery and view fault events and individual cell voltages. Download the IOS App from App Store or Android version from Google Play.

### Android

#### Cell Voltage monitor

1. Press the 3 dots on the bottom right of your Basic Info screen.
2. Login Dialog above the red line to open keyboard.
3. Enter the Login password 1234 and press Confirm. This will display each cell voltage and 8 different alarms status.
4. Touch the main screen to exit.

#### Renaming the battery

1. Press the 3 dots on the bottom right of your Basic Info screen.
2. Touch above the red line to open keyboard.
3. Enter the Login password 5678 and press Confirm.
4. Touch above the red line to open keyboard.
5. Type in the name you desire.
6. Press Confirm.

Note: After renaming, you must close the App and reopen to see the new name.

### IOS

#### Cell Voltage monitor

1. Press the 3 dots on the bottom right of your Basic Info screen.
2. Enter the password 1234 in Login Dialog and press Confirm.
3. Press Battery Information to display each cell voltage and 8 different alarms status.
4. Touch the main screen to exit.

#### Renaming the battery

1. Press the 3 dots on the bottom right of your Basic Info screen.
2. Enter the password 5678 in Login Dialog and press Confirm.
3. Press Rename Device.
4. Type in the name you desire.
6. Press Confirm.

Note: After renaming, you must close the App and reopen it to see the new name.

**LiFeBlue**  
PO<sub>4</sub>  
**Lithium Ion Battery**